

Acoustic Calibrator - Class 1



Features

- IEC 60942:2003 Class 1
- ANSI S1.40:2006
- Sound pressure level 94 dB
- Frequency 1 kHz
- Fits ½" microphones
- Adapter available for ¼" microphones

Applications

- Calibration check of Class 1 sound level meter
- Field calibration checks
- Calibration of environmental noise monitors
- Required by many noise regulations

Overview

The CR515 Acoustic Calibrator meets ANSI S1.40:2006 and IEC 60942:2003 to Class 1, the more accurate grade. It is most suited to the Class 1 sound level meters and environmental noise monitors that NoiseMeters offers.

This calibrator is included in most of the Class 1 Noise Measurement Kits and Outdoor Noise Kits, along with the sound level meter, carrying case and software where applicable. Please refer to the sound level meter web pages for more information.

Using It

As soon as the calibrator is switched on it emits a 1 kHz tone at 94 dB. The calibrator should be pushed carefully (firmly, but slowly) on to the microphone capsule.

The meter should now be adjusted accordingly. There will often be a free-field adjustment to make for the microphone in use. So, for example, you may actually be adjusting to 93.8 dB on the meter. For meters provided by NoiseMeters this is either dealt with automatically by the meter, or is covered in the meter's User Manual.

Acoustic Calibrator - Class 1

Specifications

| | | | |
|----------------------|--|---------------------|--|
| Standards | IEC 60942:2003 Class 1 ANSI S1.40:2006 | Calibration adapter | QD7 for use with 1/4" microphone capsules |
| Type Approval | PTB-1.61-4028829 LNE-24906 CEM 140786001 | Battery type | 1 x 9v (PP3, 6LR61, 6F22) |
| Sound Level | 94.0 dB \pm 0.2 dB | Dimensions | 121 x \varnothing 47 mm |
| Frequency | 1 kHz \pm 1% | Weight | 220 g with battery |
| Distortion | < 2% | Controls | Push button start, Automatic switch off with green LED indication. User override of automatic switch off |
| Reference conditions | 23°C, 101.3 kPa, 65% RH | CE classification | EN 61000-6-3:2007+A1:2011 |
| Microphone size | ½" (to IEC 1094-4) | | EN 61000-6-1:2007 |

Head Office

NoiseMeters Ltd
7 Jayes Park
Ockley
Surrey
RH5 5RR

Telephone **+44 130 677 0855**
Fax **+44 845 680 0316**

Email: **info@noisemeters.com**
Support: **support@noisemeters.com**

Web Sites

Main site:
<https://noisemeters.asia>

Product shortcut:
<https://noisemeters.asia/p/cr515/>

Tech Support:
<https://support.noisemeters.com>